

| RoboSpot MotionCamera - DMX protocol | | | |
|---|-----------|---|-----------------|
| Version: 1.1 | | | |
| Channel | DMX Value | Function | Type of control |
| 1 | | Pan (8 bit) | |
| | 0 - 255 | Pan movement by 540° (128=default) | proportional |
| 2 | | Pan Fine (16 bit) | |
| | 0 - 255 | Fine control of pan movement (0=default) | proportional |
| 3 | | Tilt (8 bit) | |
| | 0 - 255 | Tilt movement by 270° (128=default) | proportional |
| 4 | | Tilt fine (16 bit) | |
| | 0 - 255 | Fine control of tilt movement (0=default) | proportional |
| 5 | | Pan/Tilt speed , Pan/Tilt time | |
| | 0 | Standard Mode (0=default) | step |
| | 1 | Max. Speed Mode | |
| | | <i>P./T. speed-set Speed Mode in menu: Pan/Tilt Mode</i> | |
| | 2 - 255 | Speed from max. to min. | proportional |
| 6 | | Power/Special functions | |
| | 0 -19 | Reserved (0=default) <i>To activate following functions, stop in DMX value for at least 3 seconds.</i> | |
| | 20-24 | Display ON | step |
| | 25-29 | Display OFF | step |
| | 30-34 | Pan/Tilt speed mode | step |
| | 35-39 | Pan/Tilt time mode | step |
| | 40-49 | Reserved | |
| | 50-54 | Pan/Tilt reset | step |
| | 55-255 | Reserved | |
| 7 | | Reserved | |
| | 0- 255 | Raw DMX (0=default) | proportional |
| 8 | | Reserved | |
| | 0- 255 | Raw DMX (0=default) | proportional |
| Copyright © 2017 Robe Lighting s.r.o. - All rights reserved | | | |
| All Specifications subject to change without notice | | | |